

-28-

WHAT IS CLAIMED IS

5

1. An inductance device driving system which supplies a predetermined electric current to an inductance device by changing a pulse width of a voltage applied to said inductance device according to a current instruction value, said system comprising;

a current detection section which detects the electric current which flows through said inductance device;

15

a comparison section which compares a detection current value detected by said current detection section with said current instruction value;

20

a current control section which turns on/off the voltage applied to said inductance according to a comparison result of said comparison section; and

25

an off time control section which controls an off time for which application of the voltage to said inductance device is interrupted, according to the current instruction value.

30

2. The inductance device driving system as claimed in claim 1, wherein said off time control section sets the off time such that, as the current instruction value is smaller, the off time becomes longer.

35

T01260 45009660

-29-

3. The inductance device driving system
as claimed in claim 1, wherein said off time control
section sets the off time such that, as the current
instruction value is larger, the off time becomes
5 shorter.

10 4. The inductance device driving system
as claimed in claim 1, wherein said off time control
section performs bit shift of the current
instruction value so as to determine the off time
according to a value obtained from thus performed
15 bit shift of the current instruction value.

20 5. The inductance device driving system
as claimed in claim 1, further comprising an off
time information in which the off time with respect
to the current instruction value is stored, and
wherein:
25 said off time control section determines
the off time by referring to said off time
information according to the current instruction
value.

30

6. The inductance device driving system
as claimed in claim 1, wherein said off time control
35 section comprises:

a counter counting clock pulses according
to a count value set according to the current

T07260 46009660

-30-

instruction value; and

a voltage application control section
controlling application of the voltage to said
inductance device according to a count-up output of
5 said counter.

10 7. The inductance device driving system
as claimed in claim 6, wherein said off time control
section detects a timing at which the detection
current value exceeds the current instruction value,
and starts counting of said counter at the thus-
15 detected timing.

20 8. The inductance device driving system
as claimed in claim 6, wherein said voltage
application control section comprises:

a switch section controlling application
of the voltage to said inductance device from a
25 power source; and

a flywheel diode causing an electric
current generated in said inductance device when
said switch section turns from an on state into an
off state, to flow into said power source.

30

35 9. An information storage apparatus which
applies a magnetic field according to an electric
current based on a current instruction value to a
recording medium and performs at least one of

TO: 250 46009660

-31-

recording/reproducing/erasing of information to/from
said recording medium, comprising;

5 a magnetic field application section which
applies the magnetic field according to the electric
current flowing therethrough to the recording
medium;

a current detection section which detects
the electric current which flows through said
magnetic field application section;

10 a comparison section which compares a
detection current value detected by said current
detection section with said current instruction
value;

15 a current control section which turns
on/off the voltage applied to said magnetic field
application section according to a comparison result
of said comparison section; and

20 an off time control section which controls
an off time for which application of the voltage to
said magnetic field application section is
interrupted, according to the current instruction
value.

25

10. The information storage apparatus as
claimed in claim 9, wherein said off time control
section sets the off time such that, as the current
30 instruction value is smaller, the off time becomes
longer.

35

11. The information storage apparatus as
claimed in claim 9, wherein said off time control

T01260"46009660

-32-

section sets the off time such that, as the current instruction value is larger, the off time becomes shorter.

5

12. The information storage apparatus as claimed in claim 9, wherein said off time control
10 section performs bit shift of the current instruction value so as to determine the off time according to a value obtained from thus-performed bit shift of the current instruction value.

15

13. The information storage apparatus as claimed in claim 9, further comprising an off time
20 information in which the off time with respect to the current instruction value is stored, and wherein:

 said off time control section determines
the off time by referring to said off time
25 information according to the current instruction value.

30

14. The information storage apparatus as claimed in claim 9, wherein said off time control section comprises:

 a counter counting clock pulses according
35 to a count value set according to the current instruction value; and

 a voltage application control section

T31260 46009660

-33-

controlling application of the voltage to said magnetic field application section according to a count-up output of said counter.

5

15. The information storage apparatus as claimed in claim 14, wherein said off time control section detects a timing at which the detection current value exceeds the current instruction value, and starts counting of said counter at the thus-detected timing.

15

16. The information storage apparatus as claimed in claim 14, wherein said voltage application control section comprises:

a switch section controlling application of the voltage to said magnetic field application section from a power source; and

a flywheel diode causing the electric current generated in said magnetic field application section when said switch section turns from an on state into an off state, to flow into said power source.

30

17. An inductance device driving method by which a predetermined electric current is supplied to an inductance device by changing a pulse width of a voltage applied to said inductance device according to a current instruction value, comprising

-34-

the steps of;

a) detecting the electric current which flows through said inductance device;

b) comparing a detection current value
5 detected in said step a) with said current instruction value;

c) turning on/off the voltage applied to said inductance device according to a comparison result in said step b); and

10 d) controlling an off time for which application of the voltage to said inductance device is interrupted, according to the current instruction value.

15

18. The method as claimed in claim 17,
wherein, in said step d), the off time is set such
20 that, as the current instruction value is smaller, the off time becomes longer.

25

19. The method as claimed in claim 17,
wherein, in said step d), the off time is set such
that, as the current instruction value is larger,
the off time becomes shorter.

30

20. The method as claimed in claim 17,
35 wherein, in said step d), bit shift of the current instruction value is performed so that the off time is determined according to a value obtained from

T01250-16009660

-35-

thus-performed bit shift of the current instruction value.

T01250 46009660